# ARA62

# 12V PSU Module



- Supports 6-24 VDC power input.
- The AC power module of Hub 2 can be replaced.
- A round hole connector can be used externally to connect with a 2-pin terminal block.

## **Series Overview**

The PSU module is a power adapter board that is used to connect Hub2 to a 12 VDC power supply.

#### Scene

Suitable for scenes that do not have access to AC power supplies.

## **Technical Specification**

## Technical

Output Voltage	12 VDC
Maximum Load Output	1.2 A


### General

Power Supply	6–24 VDC power input	
Operating Temperature	-10 °C to +55 °C (+14 °F to +131 °F)	
Operating Humidity	10%–90% (RH)	
Product Dimensions	89 mm × 79 mm × 12 mm (3.50" × 3.11" × 0.47")	
Net Weight	34.76 g (0.08 lb)	
Gross Weight	81.11 g (0.18 lb)	
Packaging Dimensions	Single Device in inner box: 106 mm $\times$ 90 mm $\times$ 45 mm (4.17" $\times$ 3.54" $\times$ 1.77") Protective case: 339 mm $\times$ 291 mm $\times$ 261 mm (13.35" $\times$ 11.46" $\times$ 10.28")	

# **Ordering Information**

Туре	Model	Description
Alarm Accessory	ARA62	12V PSU Module

#### Installation



## Dimensions (mm[inch])

